


Light Fittings for Fluorescent Lamp

BnY81-LED Series Explosion-proof Light Fittings




- ◆ Explosion protection to
 - CENELEC
 - IEC
 - NEC
- ◆ Can be used in
 - Zone 2
 - Zone 21 and Zone 22
 - Class I, Zone 2
 - Class I, Division 2, Groups A, B, C, D
- ◆ Two enclosure types: Type I and Type II
- ◆ Applicable lamp power:
 - LED lamp tube: 9W×2, 14W×2, 28W×2
 - SMD LED: 20W, 40W, 60W
- ◆ LED light fittings: Built-in LED driver, wide voltage input, CC-CV (constant current - constant voltage) output, power factor ≥0.95.
- ◆ Emergency functions are available on request.

Catalogue number logic



Dimension drawings (all dimensions in mm) - subject to alteration



Type I: BnY81-LED 9×2□; BnY81-LED 9×2□J; BnY81-LED 14×2□; BnY81-LED 14×2□J; BnY81-LED 20□; BnY81-LED 20□J; BnY81-LED 40□



Type II: BnY81-LED 28×2□, BnY81-LED 28×2□J; BnY81-LED 40□J, BnY81-LED 60□, BnY81-LED 60□J

Zones 2; 21&22

Light Fittings for Fluorescent Lamp

BnY81-LED Series Explosion-proof Light Fittings

Technical data

Explosion-proof light fittings BnY81-LED □×□□□

Explosion protection

Global (IECEx)

IECEx CNE 24.0009X

Gas and dust

Ex ec mb IIC T5/T4 Gc¹⁾

Ex db ec mb IIC T5/T4 Gc¹⁾

Ex tb IIIC T80°C Db¹⁾

Europe (ATEX)

ACE 25 ATEX 017X

Gas and dust

Ex II 3 G Ex ec mb IIC T5/T4 Gc¹⁾

Ex II 3 G Ex db ec mb IIC T5/T4 Gc¹⁾

Ex II 2 D Ex tb IIIC T80°C Db¹⁾

¹⁾ See Selection Table

Certificates

IECEx; ATEX

Conformity to standards

EN 60079-0, EN 60079-1, EN 60079-7, EN 60079-18, EN 60079-31

IEC 60079-0, IEC 60079-1, IEC 60079-7, IEC 60079-18, IEC 60079-31

Material

Enclosure

GRP, stands 7J impact, corrosion-proof

Diffuser

Polycarbonate, high light transmission, stands 7J impact

LED driver

Wide voltage input, CC-CV (constant current - constant voltage) output, power factor ≥0.95, with function of distributed current, constant current, surge-proof and anti-electromagnetic interference, and protection against overcurrent, open circuit, and short circuit.

Exposed fastener

Stainless steel

Lamp

Lamp specification

LED lamp tube, SMD LED

Lamp power (W)

LED lamp tube: 9W×2, 14W×2, 28W×2

SMD LED: 20W, 40W, 60W

Rated voltage

100~277V AC 50/60Hz; 130~250V DC

Degree of protection

IP66

Ambient temperature

-40°C~+60°C(+58°C)(+40°C)

Terminal

3×1.5~4mm² (L+N+PE)

Mounting

Ceiling type, pendant pole type, pendant chain type, wall type, pole type

Cable entries

Pole type: 1×Φ26: 1×M25×1.5 cable glands (DQM-I/I Ex eb, plastic).

Other mounting methods: 2×Φ26: 2×M25×1.5 cable glands (DQM-I/I Ex eb, plastic).

Φ9~Φ16(mm);

Available cable outer diameter

Emergency data

Emergency unit

Special emergency controller and battery pack, with protection against overcharge and overdischarge

Emergency power (W)

9W×2×77%, 14W×2×50%, 28W×2×25%

20W×70%, 40W×35%, 60W×23%

Emergency starting time

0.3s

Charging time

24h

Emergency lighting time

90min (180min is optional)



Selection table

Rated power(W)	Temperature classification							
	For non-emergency type				For emergency type			
	-40°C≤Ta≤+40°C		-40°C≤Ta≤+60°C		-40°C≤Ta≤+40°C		-40°C≤Ta≤+58°C	
	Gas	Dust	Gas	Dust	Gas	Dust	Gas	Dust
9×2, 14×2, 28×2	T5	T80°C	T4	T80°C	T5	T80°C	T4	T80°C
20, 40, 60	T5	T80°C	T4	T80°C	T5	T80°C	T4	T80°C

Light Fittings for Fluorescent Lamp

BnY81-LED Series Explosion-proof Light Fittings

Selection table


Type / Ordering code	Lamp power(W)	Weight (kg)	Type / Ordering code	Lamp power(W)	Weight (kg)	Type / Ordering code	Lamp power(W)	Weight (kg)
BnY81-LED 9×2X	9 × 2	3.60	BnY81-LED 14×2X	14×2	3.60	BnY81-LED 28×2X	28×2	6.00
BnY81-LED 9×2G	9 × 2	4.00	BnY81-LED 14×2G	14×2	4.00	BnY81-LED 28×2G	28×2	6.40
BnY81-LED 9×2D	9 × 2	3.50	BnY81-LED 14×2D	14×2	3.40	BnY81-LED 28×2D	28×2	5.90
BnY81-LED 9×2B	9 × 2	4.00	BnY81-LED 14×2B	14×2	4.00	BnY81-LED 28×2B	28×2	6.50
BnY81-LED 9×2L	9 × 2	3.80	BnY81-LED 14×2L	14×2	3.80	BnY81-LED 28×2L	28×2	6.30
BnY81-LED 9×2XJ	9 × 2	5.50	BnY81-LED 14×2XJ	14×2	5.50	BnY81-LED 28×2XJ	28×2	7.60
BnY81-LED 9×2GJ	9 × 2	5.50	BnY81-LED 14×2GJ	14×2	5.80	BnY81-LED 28×2GJ	28×2	8.00
BnY81-LED 9×2DJ	9 × 2	5.30	BnY81-LED 14×2DJ	14×2	5.30	BnY81-LED 28×2DJ	28×2	7.40
BnY81-LED 9×2BJ	9 × 2	5.90	BnY81-LED 14×2BJ	14×2	5.90	BnY81-LED 28×2BJ	28×2	8.00
BnY81-LED 9×2LJ	9 × 2	5.60	BnY81-LED 14×2LJ	14×2	5.60	BnY81-LED 28×2LJ	28×2	7.80
BnY81-LED 20X	20	3.50	BnY81-LED 40X	40	4.10	BnY81-LED 60X	60	6.20
BnY81-LED 20G	20	3.90	BnY81-LED 40G	40	4.50	BnY81-LED 60G	60	6.50
BnY81-LED 20D	20	3.30	BnY81-LED 40D	40	3.90	BnY81-LED 60D	60	6.00
BnY81-LED 20B	20	4.00	BnY81-LED 40B	40	4.50	BnY81-LED 60B	60	6.60
BnY81-LED 20L	20	3.70	BnY81-LED 40L	40	4.30	BnY81-LED 60L	60	6.30
BnY81-LED 20XJ	20	5.30	BnY81-LED 40XJ	40	7.80	BnY81-LED 60XJ	60	7.80
BnY81-LED 20GJ	20	5.70	BnY81-LED 40GJ	40	8.10	BnY81-LED 60GJ	60	8.10
BnY81-LED 20DJ	20	5.20	BnY81-LED 40DJ	40	7.60	BnY81-LED 60DJ	60	7.60
BnY81-LED 20BJ	20	5.80	BnY81-LED 40BJ	40	8.20	BnY81-LED 60BJ	60	8.20
BnY81-LED 20LJ	20	5.50	BnY81-LED 40LJ	40	7.90	BnY81-LED 60LJ	60	7.90

Note: 1. Products above include all the mounting accessories listed in Mounting Accessories & Spare Parts Table (see P2/43).

Photometric data


BnY81-LED 9×2□

Lamp power (W)	9×2
Rated luminous flux	2948lm
Wattage	20W




BnY81-LED 14×2□

Lamp power (W)	14×2
Rated luminous flux	4224lm
Wattage	27.9W




BnY81-LED 28×2□

Lamp power (W)	28×2
Rated luminous flux	8690lm
Wattage	56.7W




BnY81-LED 20□

Lamp power (W)	20
Rated luminous flux	3263lm
Wattage	21.3W




BnY81-LED 40□

Lamp power (W)	40
Rated luminous flux	5848lm
Wattage	39.7W



BnY81-LED 60□

Lamp power (W)	60
Rated luminous flux	8617lm
Wattage	56.7W



We can provide lighting design and data by professional lighting software DIALUX based upon simulated site situation on request.




Light Fittings for Fluorescent Lamp

BnY81-LED Series Explosion-proof Light Fittings


Mounting type (all dimensions in mm) - subject to alteration

Installation reference


D: pendant chain type




G: pendant pole type




X: ceiling type



B: wall type



L: pole type (the pole is provided by user)



Mounting Accessories & Spare Parts Table

Supplied according to the mounting type

Mounting type	Accessories			Ordering code	Weight (kg)
	Name	Qty	Illustration		
D: pendant chain type	①.Sucker	2	See P2/6	5136017	0.15
	②.Chain	2	Length: 450mm	5136016	0.08
G: pendant pole type	③.Mounting bracket	2	Stainless steel, see P2/6	51S01G1	0.04
	④.M8 Screw	2	Stainless steel, length: 350mm	51S01G2	0.12
X: ceiling type	⑤.Mounting bracket	2	Stainless steel, see P2/7	5136015	0.20
B: wall type	⑥.Wall bracket	2	Stainless steel, welded sheet steel	5236B02	0.25
L: pole type	⑦.G1 1/2" Pipe clamp	2	Stainless steel, see P2/7	5136014	0.04
	⑧.Mounting bracket	2	Stainless steel, see P2/7	5136012	0.04

Note: Accessories not in the table shall be supplied by user.